



Input Frequency 50/60 Hz Rated Output Power 500 Watts Note: All measurements were taken with input voltage at 115 V nominal and 60 Hz.

Input AC Current Waveform (ITHD = 31.44%, 50% Load)

I <sub>RMS</sub>	PF	I <sub>THD</sub> (%)	Load	Fraction	Input	DC Terminal Voltage (V)/ DC Load Current (A)					Output	Efficiency
Α			(%)	of Load	Watts	12V (cumulative of 12V1, 12V2, etc.)	-12V	3.3V	5V*	5VSB	Watts	%
1.09	0.96	25.75%	20%	Light	120.46	12.2/6.8	11.3/0.1	3.3/2.4	5.1/1.6	5.1/0.5	101.99	84.66%
2.70	0.95	31.44%	50%	Typical	294.32	12.2/16.8	11.3/0.2	3.3/5.9	5.1/4	5.1/1.2	253.28	86.06%
5.46	0.97	24.96%	100%	Full	607.35	12.1/33.6	11.4/0.5	3.3/11.9	5.1/7.9	5/2.5	503.44	82.89%







PLUG LOAD Solutions These tests were conducted by a third party independent testing firm on behalf of the 80 PLUS Program. 80 PLUS is a certification program to promote highly-efficient power supplies (greater than 80% efficiency in the active mode) in technology applications. http://www.80plus.org/

