## **80 PLUS Verification and Testing Report**


TYPICAL EFFICIENCY (50% Load): AVERAGE EFFICIENCY : 80 PLUS COMPLIANT: 83.50% 81.53% YES


Esse ID #	1000
Ecos ID #	1060
Manufacturer	FSP
Model Number	FSP300-60GHS
Serial Number	S8381000008
Year	2008
Туре	SFX12V
Test Date	10/16/2008

Rated Specifications	Value	Units	
Input Voltage	100-240	Volts	
Input Current	4.5-2.5	Amps	
Input Frequency	50-60	Hz	
Rated Output Power	300	Watts	

Note: All measurements were taken with input voltage at 115 V nominal and 60 Hz.

								•		,	,	,
I <sub>RMS</sub>	PF	I <sub>THD</sub> (%)	Load	Fraction	Input	DC Terminal Voltage (V)/ DC Load Current (A)						Efficiency
Α			(%)	of Load	Watts	12V (cumulative of 12V1, 12V2, etc.)	-12V	3.3V	5V*	5VSB	Watts	%
0.67	0.98	16.2%	20%	Light	75	11.9/3.2	11.9/0.1	3.4/2.1	5.1/2.3	5.1/0.4	60	80.16%
1.63	0.96	27.6%	50%	Typical	180	11.9/8.1	11.9/0.2	3.4/5.2	5.1/5.7	5/0.9	150	83.50%
3.32	0.96	26.0%	100%	Full	368	11.9/16.2	12/0.4	3.3/10.4	5/11.5	4.8/1.8	298	80.92%








These tests were conducted by a third party independent testing firm on behalf of the 80 PLUS® Program. 80 PLUS is a certification program to promote highly-efficient power supplies (greater than 80% efficiency in the active mode) in technology applications. *http://www.80plus.org/* 







Input AC Current Waveform (ITHD = 27.58%, 50% Load)